

PTZ Camera Controller

The ideal solution for education, conferencing, telemedicine, livestreaming & broadcasting!

The AVer CL01 is a professional PTZ camera controller with a robust communication interface, built-in VISCA and Pelco-D/P protocols. It supports RS-422 / RS-485 / RS-232 / IP control for compatibility with most PTZ cameras. Simple configuration makes it easy to operate the 7 camera shortcut channels, 3 infinite rotation knobs, and more.



CONTROL 7 PTZ CAMERAS



MULTIPLE CONTROL INTERFACES

VISCA PELCO-D/P

AVer CL01



AVer CL01

— PTZ Camera Controller

 Item code
 60S3300000AB

 EAN code
 4719552125753

Product Specifications

· I/O Interface

Communication RS-485, RS-422, RS-232, IP, Micro USB for firmware upgrades Baud Rate 2400, 4800, 9600, 19200, 38400 bps > User Interface
Display OLED display screen Rotation Button 3
Camera Shortcut Channel 7 Joystick 1
· Camera Control
IP Address Default: 192.168.1.162 / 163 / 164 / 165 / 166 / 167 / 168 (from Cam 1 to Cam 7) UDP Port 08090
Cam ID 1 to 7 and more (255 max.) Control Protocol VISCA, SONY VISCA , Pelco-D/P, UDP, IP (VISCA over 1000)
· System
Operating Temperature 0°C ~ 40°C (32°F ~ 104°F) Dimensions 173 mm (W) x 99 mm (H) x 350 mm (D)
Gross Weight 2.5 kg Power Source DC 12V/2A, AC 100-240V
Power Consumption 24 W Application Indoor
Package Content User manual / 4-pin RS485 terminal / power adapter

Hardware Specifications

Front Panel

c () -	
	AVer

Back Panel

Distributor/Dealer



AVer

©2019 AVer Information Europe B.V. All rights reserved. All brand names and logos are trademarks of their respective companies.

www.avereurope.com

